



Europäisches  
Patentamt

European  
Patent Office

Office européen  
des brevets

REC'D 28 FEB 2001

WIPO

PCT

EPO - DG 1

05. 02. 2001

(90)

Bescheinigung

Certificate

Attestation

Die angehefteten Unterla-  
gen stimmen mit der  
ursprünglich eingereichten  
Fassung der auf dem näch-  
sten Blatt bezeichneten  
europäischen Patentanmel-  
dung überein.

The attached documents  
are exact copies of the  
European patent application  
described on the following  
page, as originally filed.

Les documents fixés à  
cette attestation sont  
conformes à la version  
initialement déposée de  
la demande de brevet  
européen spécifiée à la  
page suivante.

Patentanmeldung Nr. Patent application No. Demande de brevet n°

00200094.1

## PRIORITY DOCUMENT

SUBMITTED OR TRANSMITTED IN  
COMPLIANCE WITH RULE 17.1(a) OR (b)

Der Präsident des Europäischen Patentamts;  
Im Auftrag

For the President of the European Patent Office

Le Président de l'Office européen des brevets  
p.o.

I.L.C. HATTEN-HECKMAN

DEN HAAG, DEN  
THE HAGUE, 11/01/01  
LA HAYE, LE

**THIS PAGE BLANK (USPTO)**



Europäisches  
Patentamt

European  
Patent Office

Office européen  
des brevets

**Blatt 2 der Bescheinigung**  
**Sheet 2 of the certificate**  
**Page 2 de l'attestation**

Anmeldung Nr.:  
Application no.:  
Demande n°: 00200094.1

Anmeldetag:  
Date of filing:  
Date de dépôt: 12/01/00

Anmelder:  
Applicant(s):  
Demandeur(s):  
Koninklijke Philips Electronics N.V.  
5621 BA Eindhoven  
NETHERLANDS

Bezeichnung der Erfindung:  
Title of the invention:  
Titre de l'invention:  
Image data compression

In Anspruch genommene Priorität(en) / Priority(ies) claimed / Priorité(s) revendiquée(s)

Staat:  
State:  
Pays:

Tag:  
Date:  
Date:

Aktenzeichen:  
File no.  
Numéro de dépôt:

Internationale Patentklassifikation:  
International Patent classification:  
Classification internationale des brevets:

/

Am Anmeldetag benannte Vertragsstaaten:  
Contracting states designated at date of filing: AT/BE/CH/CY/DE/DK/ES/FI/FR/GB/GR/IE/IT/LI/LU/MC/NL/PT/SE/TR  
Etats contractants désignés lors du dépôt:

Bemerkungen:  
Remarks:  
Remarques:

**THIS PAGE BLANK (USPTO)**

Image data compression.

EPO - DG 1

12. 01. 2000

(75)

The invention relates to a method, a device and a transmitter, in which an image signal is encoded to obtain a bit-stream. The invention further relates to transcoding. The invention also relates to a receiver, a bit-stream and a storage medium.

5

EP-0 514 663 A2 discloses an apparatus and method for motion video encoding employing an adaptive quantizer. The MPEG video standard defines a layered architecture for compressing a video sequence. First, a sequence of video pictures is subdivided into disjoint Groups Of Pictures (GOPs). Each GOP is compressed independently of other GOP's to facilitate random access to any picture and also to limit the propagation of transmission errors. Every picture in a GOP is subdivided into Macro-Blocks (MBs). For a color picture, an MB is a collection of 16x16 luminance pixels and two 8x8 blocks of chrominance pixels. In MPEG, the two chrominance components are both sampled at half the horizontal and vertical resolution of the luminance. As such, an MB completely describes a 16x16 color segment of a picture. In an MB the 16x16 luminance pixels are further subdivided into four luminance blocks of 8x8 pixels. The still or motion picture data in the form of MBs, represented by either the actual pixel data (intra-mode) or only the error data (predictive mode), is inputted to a transformation. This transformation is a two-dimensional Discrete Cosine Transform (DCT) applied to each of the MBs. After applying the DCT, the resulting coefficients undergo a quantization step. The DCT transform coefficients are uniformly quantized with a matrix of quantization steps. MPEG specifies one of two reference matrices from which the quantization steps may be derived. The choice of which matrix is used, depends on the MB mode. Although the reference matrices can be defined by the encoder at the beginning of a video sequence, they remain fixed afterwards. MPEG allows dynamic changes to the matrix of quantization steps, however, by allowing a scaling factor for the reference matrices. This scaling factor can be changed for every MB. The adaptation of this scaling factor is performed on an MB to MB basis and varies based on the complexity of the image and the available rate control requirements.

An object of the invention is to provide further compression. To this end, the invention provides a method, a device, a transmitter, a transcoder, a receiver, a bit-stream and a storage medium as defined in the independent claims. Advantageous embodiments are defined in the dependent claims.

5 In a first embodiment of the invention, blocks of transform coefficients are provided and high-frequency transform coefficients are attenuated. The invention is based on the insight that especially for obtaining low bit-rates, attenuating high-frequency transform coefficients is more advantageous than increasing a step-size for all transform coefficients. Increasing the step-size causes accumulation of errors in predictively coded pictures, because  
10 each predictively coded picture is predicted from a previous picture. In this way, errors will accumulate over a GOP. A resulting coding artifact can be seen as "breathing" of the picture quality over a time interval of a GOP which is normally about half a second. The invention provides further compression by attenuation of high-frequency coefficients. Lower frequencies are less or not attenuated. Preferably, some of the coefficients of lower frequencies remain  
15 unaffected. The accumulation of errors is herewith reduced.

For attenuating high frequency coefficients, the invention provides a curve with higher quantization step for higher-frequency transform coefficients. Because no curve information is put in the resulting bit-stream, the reconstruction is performed by using an original quantization scaling factor only. The quantization according to the invention can be  
20 seen as additional quantization, which is not taken into account in a reconstruction. Therefore, a reconstructed coefficient will have a lower value than an original coefficient.

The bit rate can easily be regulated by shifting the curve to lower or higher frequencies and/or multiplying the curve.

The aforementioned and other aspects of the invention will be apparent from  
25 and elucidated with reference to the embodiments described hereinafter.

In the drawings:

Fig. 1 shows a block of transform coefficients;

Fig. 2 shows an illustration of perceived picture quality as function of time  
30 when a higher step-size is used to encode an image signal;

Fig. 3 shows a preferred quantization curve according to the invention;

Fig. 4 shows an embodiment of a transmitter according to the invention; and

Fig. 5 shows an embodiment of a receiver according to the invention.

The drawings only show those elements that are necessary to understand the invention.

Fig. 1 shows a block of transform coefficients. These coefficients  $C_i$  are  
5 obtained by transforming a block of data from a spatial domain to a frequency domain. In this example, a picture is encoded per block of 8 by 8 pixels. The result of the transformation is a block of 8 by 8 transform coefficients (so  $i = 0 \dots 63$ ). From the left to the right in the block, the horizontal spatial frequency increases. From the top to the bottom, the vertical spatial frequency increases. The upper-left coefficient  $C_0$  represents a DC coefficient. Although  
10 various transformations may be used, preferably DCT transformation is performed. In Fig. 1, a zigzag scanning is used to obtain an order of transform coefficients  $C_i$ . Although another scanning may be used, zigzag scanning is widely used, e.g. in MPEG.

In MPEG, coefficients  $C_i$  are quantized by dividing them by a weight in a predefined quantization matrix and by a quantization scaling factor. The quantization scaling  
15 factor is adapted per macro block. The weights in the quantization matrix are so arranged that the less important coefficients are coded with less accuracy.

One way of reducing a bit rate would be to use a higher quantization scaling factor. Errors introduced by using a higher quantization scaling factor affect the picture quality. In a predictive coding method, like MPEG, errors in a given picture affect another  
20 picture when the given picture is used to predict the other picture. The degradation of intra-coded pictures is usually limited.

An error made in a picture that is used as a predictor is forwarded to a predicted picture. Accumulation of errors takes place, depending on the number of predictions that is made. The accumulation of errors gives rise to annoying effects. An effect is illustrated in Fig.  
25 2. A Perceived picture quality  $P_{pq}$  is shown as function of time  $t$ . The perceived picture quality  $P_{pq}$  between a beginning and an end of a GOP differs significantly. This effect may be called "breathing", i.e. the  $P_{pq}$  decreases during a GOP and increases suddenly with a new, refreshing I picture.

Attenuating high-frequency coefficients  $C_i$  according to the invention reduces  
30 this accumulation of errors. The coefficients are quantized with an additional quantization step size  $Q_{ADD}$ . Because this additional quantization step-size is not put in the resulting bit-stream, the reconstruction is performed with the quantization scaling factor and the quantization matrix without taking into account the additional quantization. Therefore, a reconstructed coefficient will have a lower value than an original coefficient  $C_i$ . As a result, the coefficient

$C_i$  has been attenuated. To reflect the lower importance of higher frequencies, the DCT coefficients are quantized with a variable quantization step depending on their position. Fig. 3 shows a curve QC showing the additional quantization step size  $Q_{ADD}$  as a function of a position of the quantized transform coefficient  $C_i$ . The quantization step  $Q_{ADD}$  gradually increases for higher-frequency transform coefficients  $C_i$ . The lowest coefficients  $C_i$  are not affected, keeping their value from the incoming stream. This is done to protect the low frequencies to which the eye is very sensible. In a practical embodiment 8 coefficients always remain unaffected. Keeping the lower frequencies unaffected, is advantageous in preventing the accumulation of errors.

It would have been possible to remove every coefficient after a given position in the DCT coefficient order. However, due to a particularity of the DCT, that would have given rise to a deterioration of lower frequencies. In fact, the DCT is a kind of bank filter, which extracts a value for a range of frequencies, i.e. a DCT coefficient. The bank filter is however imperfect in that frequency ranges overlap each other. This means that a DCT coefficient contains energy in a quite large band. Therefore, quantizing a coefficient has some repercussions on lower frequencies. Thus, removing complete coefficients after a given position would not only remove the energy contained in high frequencies but also some energy contained in lower frequencies, because even a high frequency coefficient contains energy in lower frequencies. Attenuating is therefore better than removing transform coefficients  $C_i$ . A smoothly increasing step-size is advantageous regarding the removing of energy from lower frequencies. In a practical embodiment, a logarithmic function is used.

For bit rate control, the curve QC may be shifted. The curve QC is shifted to the left to reduce the bit rate and shifted to the right to increase the bit rate. Preferably, some lower frequency transform coefficients should not be additionally quantized. If lower frequencies remain untouched, less errors are accumulated.

For further bit rate control, the curve QC may be multiplied by a certain multiplier. In case the multiplier is larger than one, the coefficients are more coarsely quantized and the bit rate is further reduced. In case the multiplier is smaller than one, the coefficients are less coarsely quantized and the bit rate is increased. Shifting and multiplying may be performed in combination or independently.

Advantage may be taken from the prediction tree to avoid the propagation of errors. Instead of quantizing pictures heavily at the beginning of a prediction sequence, it is advantageous to quantize last pictures in a prediction sequence more heavily. In this way, predictions are made from rather good images. In a GOP with one I (intra-coded) picture



followed by P (predictively coded) pictures, a last P picture may be quantized more heavily. Since about 25 pictures are displayed per second, one picture is displayed for only 0.04 second. During this very short lap of time, the human eye does not observe a drop in quality. Squeezing the last P picture is possible resulting in an extreme low number of bits used. The current P picture is of low quality, but this is no problem because the viewer does not notice the drop in quality and the last P picture is not used to predict another picture. This strategy can also be used for B (bi-directional predictively coded) pictures as they are also at an end of a prediction sequence. Generally, the B-pictures cannot be quantized as coarsely as the last P-picture, since there are more than one B pictures in a GOP and repetitive drops in quality within a GOP tend to lower the global quality of the image as perceived. This strategy does not cause a breathing effect because errors that are forwarded to other pictures are smaller. Although it is possible to quantize more than one last P-picture more coarsely, this is less advantageous.

As discussed above, quantizing pictures more coarsely can be achieved by shifting or multiplying the quantization curve.

Fig. 4 shows an embodiment of a transmitter according to the invention. The transmitter 1 comprises means for obtaining a signal S, e.g. a camera 10. The transmitter further comprises an encoding device 2. Although not necessary to the invention, the encoding device preferably encodes the image signal by using motion estimation and motion compensation. The device 2 therefore comprises a motion compensator 11 and a motion estimator 18. The motion compensated signal is transform coded in transform coder 12. This transform coder preferably applies a DCT transformation on the motion compensated signal. After the transformation, the transformed signal is quantized in quantizer Q 13. This is a standard quantization as is known from the prior art. To perform motion estimation, a reconstructed picture is necessary. Therefore, the device 2 comprises an inverse quantizer IQ 14 and an inverse transform coder IDCT 15 that perform inverse operations of Q 13 and DCT 12 respectively. In the inverse motion compensator IMC 16 that is coupled to the ME 18 the reconstructed picture is obtained. The reconstructed picture is stored in the picture memory MEM 17. The reconstructed picture is used for motion estimation in a next picture that has to be encoded. The quantized motion compensated signal as obtained in Q 13 is furnished to an additional quantizer Q<sub>ADD</sub> 19 according to the invention. The Q<sub>ADD</sub> 19 applies an additional quantization to the signal with a curve as shown in Fig. 3. The signal is thereafter encoded in the Variable Length Encoder VLE 20 to obtain a video elementary stream V. A bit rate R of the video stream V is derived in VLE 20 and furnished to CPU 21. The CPU 21 is coupled to

Q<sub>ADD</sub> 19 to control the bit rate by shifting and/ or multiplying the curve. The CPU 21 also controls other parts of the device 2. Q<sub>ADD</sub> may be defined for blocks of 8x8 pixels. The quantization scale factor used in Q 13 is defined per macroblock.

The Q<sub>ADD</sub> is preferably located outside the encoding loop MC 11...ME 18. This  
5 means that e.g. for motion compensation, a better quality is available than from the additionally quantized signal. This is important, because a good quality of the reconstructed picture means that better encoding can be obtained, in the case of motion compensation due to a better motion estimation. The better motion estimation is performed, the better is the compression of the signal S. The video stream V is multiplexed with other streams, e.g. an  
10 audio elementary stream A in a multiplexer 22 to obtain a transport/ program stream TS.

Coding bit-streams from an original bit-rate R1 to a new bit-rate R2 is called bit-rate transcoding. Bit-rate transcoding is e.g. performed to unify incoming bit-streams that vary in bit-rate. Further, the bit rates used for broadcasting are usually too high for storage on digital storage media, given the condition that enough playing time should be available.  
15 Therefore, bit rate reduction is often necessary. Furthermore, for implementation of long-play mode a low bit rate is required. The invention is preferably applied in a bit rate transcoder. Such a bit rate transcoder may be included in a digital video recorder.

Fig. 5 shows an embodiment of a receiver (e.g. digital video recorder, like D-VHS). The receiver 3 comprises receiving means 4 and a bit rate transcoder 5. An incoming  
20 transport/ program stream TS1 is received in receiving means 4, e.g. an antenna system, and thereafter demultiplexed in a demultiplexer 50 to obtain a video elementary stream V1 and an audio elementary stream A1. The transport stream TS1 may be transmitted by an embodiment as shown in Fig. 4. The video elementary stream V1 is passed to a Variable Length Decoder (VLD) 51 to obtain blocks of transform coefficients C<sub>i</sub>. The audio elementary stream A1 is  
25 bypassed because transcoding an audio elementary stream will hardly affect the bit rate. After the VLD 51, the decoded video stream is furnished to a quantizer Q<sub>ADD</sub> 52 according to the invention. In Q<sub>ADD</sub> 52, the higher frequency coefficients are attenuated as explained above. The additional quantized video stream is furnished to a Variable Length Encoder (VLE) 53 to obtain a new video elementary stream V2. As in Fig. 4, a bit rate R2 is derived in the VLE 53  
30 and furnished to a CPU 54 to control the Q<sub>ADD</sub> 52. The new video stream V2 is multiplexed together with the parsed audio stream A1 in a multiplexer 55 to obtain a new transport stream TS2. The new transport stream TS2 has a lower bit rate than the incoming transport stream TS1. The new transport stream TS2 may be stored on a storage medium 6. The storage medium 6 may be a DVD, a CD-ROM, a (D-VHS) tape, etc.

Due to the extreme low complexity of the proposed algorithm, especially for transcoding, it is well suited for applications, which demand high throughput, like High Definition bit-streams. HD bit-streams can be re-quantized to a lower bit-rate, while the resolution remains the same. A preferred application of the invention reduces the bit-rate of an HD-stream for storing the lower bit-rate HD-stream on a storage medium. Another preferred application is a long play mode in Standard Definition (SD).

It should be noted that the above-mentioned embodiments illustrate rather than limit the invention, and that those skilled in the art will be able to design many alternative embodiments without departing from the scope of the appended claims. The word 'picture' also refers to frame, field, etc. In the claims, any reference signs placed between parentheses shall not be construed as limiting the claim. The word 'comprising' does not exclude the presence of other elements or steps than those listed in a claim. The invention can be implemented by means of hardware comprising several distinct elements, and by means of a suitably programmed computer. In a device claim enumerating several means, several of these means can be embodied by one and the same item of hardware. The mere fact that certain measures are recited in mutually different dependent claims does not indicate that a combination of these measures cannot be used to advantage.

In summary, a method and a device are provided, wherein a signal is encoded to obtain a bit-stream. Blocks of quantized transform coefficients are provided. Transform coefficients corresponding to higher frequencies are attenuated. For attenuating high frequency coefficients, the invention provides a curve QC with higher quantization step-size  $Q_{ADD}$  for transform coefficients  $C_i$  corresponding to higher frequencies. Because this additional quantization step size  $Q_{ADD}$  is not put in the resulting bit-stream, a reconstruction is performed with an original quantization step step-size, without taking the additional quantization into account. Therefore, a reconstructed coefficient will have a lower value than an original coefficient  $C_i$ . Bit rates can easily be regulated by shifting the curve QC to lower or higher frequencies and/or multiplying the curve QC.

**THIS PAGE BLANK (USPTO)**

## CLAIMS:

12. 01. 2000

(75)

1. A method of encoding (2) a signal (S) to obtain a bit-stream (V,TS), the method comprising the steps of:

providing (12,13) blocks of quantized transform coefficients ( $C_i$ ); and  
attenuating (19) high-frequency transform coefficients ( $C_i$ ) of a given block.

5

2. A method as claimed in claim 1, the step of attenuating comprising:  
quantizing (19) the transform coefficients ( $C_i$ ) of the given block with a curve (QC) having higher quantization steps ( $Q_{ADD}$ ) for higher-frequency transform coefficients ( $C_i$ ), without putting information concerning said curve (QC) into the bit-stream (V,TS).

10

3. A method as claimed in claim 2,  
further comprising the step of shifting (19,21) the curve (QC) to adjust a bit rate (R) of the bit-stream (V,TS).

15

4. A method as claimed in claim 2,  
further comprising the step of multiplying (19,21) the curve (QC) to adjust a bit rate (R) of the bit-stream (V,TS).

20

5. A method as claimed in claim 2, wherein the signal (S) comprises intra-coded and predictively coded pictures, the method comprising the step of:  
quantizing (19,21) predictively coded pictures at an end of a prediction sequence more coarsely than predictively coded pictures at a start of the prediction sequence.

25

6. A method as claimed in claim 1, the method further comprising the steps of:  
decoding (14,15) the blocks of quantized transform coefficients ( $C_i$ ) to obtain a reconstructed picture rather than decoding (14,15) the attenuated (19) high-frequency transform coefficients ( $C_i$ ).

7. A device (2) for encoding a signal (S) to obtain a bit-stream (V,TS),  
comprising:

means (12,13) for providing blocks of quantized transform coefficients ( $C_i$ );

and

5 means (19) for attenuating high-frequency transform coefficients ( $C_i$ ) of a given  
block.

8. A transmitter (1) comprising:

means (10) for obtaining a signal (S); and

10 a device (2) for encoding the signal (S) as claimed in claim 7.

9. A method of transcoding (5) an encoded signal (TS1,V1), comprising the steps  
of:

15 decoding (50,51) the encoded signal (TS1,V1) to obtain blocks of quantized  
transform coefficients ( $C_i$ ); and

attenuating (52) high-frequency transform coefficients ( $C_i$ ) of a given block.

10. A bit rate transcoder (5) for transcoding an encoded signal (TS1,V1)  
comprising:

20 means (50,51) for decoding the encoded signal (TS1,V1) to obtain blocks of  
quantized transform coefficients ( $C_i$ ); and

means for attenuating (52) high-frequency transform coefficients ( $C_i$ ) of a given  
block.

25 11. A receiver (3) comprising:

means (4,50) for obtaining an encoded signal (TS1,V1); and

a bit rate transcoder (5) for transcoding the encoded signal (TS1,V1) as claimed  
in claim 10.

30 12. A bit-stream (V,TS,V2,TS2) comprising blocks of quantized transform  
coefficients ( $C_i$ ), wherein high-frequency transform coefficients ( $C_i$ ) of a given block have  
been attenuated.

13. A storage medium (6) on which a bit-stream (V,TS,V2,TS2) as claimed in claim 12 is stored.

**THIS PAGE BLANK (USPTO)**



## ABSTRACT:

12. 01. 2000

(75)

A method and a device are provided, in which a signal is encoded to obtain a bit-stream. Blocks of quantized transform coefficients are provided. Transform coefficients corresponding to higher frequencies are attenuated. For attenuating high frequency coefficients, the invention provides a curve (QC) with higher quantization step-size ( $Q_{ADD}$ ) for transform coefficients ( $C_i$ ) corresponding to higher frequencies. Because this additional quantization step size ( $Q_{ADD}$ ) is not put in the resulting bit-stream, the reconstruction is performed with an original quantization step-size, without taking the additional quantizing into account. Therefore, a reconstructed coefficient will have a lower value than an original coefficient ( $C_i$ ). Bit rates can easily be regulated by shifting the curve (QC) to lower or higher frequencies and/or multiplying the curve (QC).

Fig. 3

**THIS PAGE BLANK (USPTO)**

12. 01. 2000

(75)

1/3

C <sub>0</sub>	C <sub>1</sub>	C <sub>5</sub>	C <sub>6</sub>	C <sub>14</sub>	C <sub>15</sub>	C <sub>27</sub>	C <sub>28</sub>
C <sub>2</sub>	C <sub>4</sub>	C <sub>7</sub>	C <sub>13</sub>	C <sub>16</sub>	C <sub>26</sub>	C <sub>29</sub>	C <sub>42</sub>
C <sub>3</sub>	C <sub>8</sub>	C <sub>12</sub>	C <sub>17</sub>	C <sub>25</sub>	C <sub>30</sub>	C <sub>41</sub>	C <sub>43</sub>
C <sub>9</sub>	C <sub>11</sub>	C <sub>18</sub>	C <sub>24</sub>	C <sub>31</sub>	C <sub>40</sub>	C <sub>44</sub>	C <sub>53</sub>
C <sub>10</sub>	C <sub>19</sub>	C <sub>23</sub>	C <sub>32</sub>	C <sub>39</sub>	C <sub>45</sub>	C <sub>52</sub>	C <sub>54</sub>
C <sub>20</sub>	C <sub>22</sub>	C <sub>33</sub>	C <sub>38</sub>	C <sub>46</sub>	C <sub>51</sub>	C <sub>55</sub>	C <sub>60</sub>
C <sub>21</sub>	C <sub>34</sub>	C <sub>37</sub>	C <sub>47</sub>	C <sub>50</sub>	C <sub>56</sub>	C <sub>59</sub>	C <sub>61</sub>
C <sub>35</sub>	C <sub>36</sub>	C <sub>48</sub>	C <sub>49</sub>	C <sub>57</sub>	C <sub>58</sub>	C <sub>62</sub>	C <sub>63</sub>

FIG. 1




FIG. 2

2/3




FIG. 3




FIG. 4




FIG. 5

**THIS PAGE BLANK (USPTO)**